



192.168.1.1



الدخول لمتصفح google chrome وتسجيل ip
الراوتر بالبحث 192.168.1.1

تسجيل الدخول

يتطلب http://192.168.1.1 اسم مستخدم وكلمة مرور. اتصالك
بموقع الويب هذا لا يتمتع بخصوصية
اسم المستخدم

admin

كلمة المرور

•••••

تسجيل الدخول

إلغاء

D-Link

1

DSL-124

SETUP

ADVANCED

MAINTENANCE

STATUS

HELP

Wizard

Local Network

Internet Setup

Wireless Setup

Time and Date

SETTING UP YOUR INTERNET

There are two ways to set up your Internet connection. You can use the Web-based Internet Connection Setup Wizard or you can manually configure the connection.

Please make sure you have your ISP's connection settings first if you choose manual setup.

INTERNET CONNECTION WIZARD

You can use this wizard for assistance and quick connection of your new D-Link Router to the Internet. You will be presented with step-by-step instructions in order to get your Internet connection up and running. Click the button below to ~~begin~~.

2

Note: Before launching the wizard, please ensure you have correctly followed the steps outlined in the Quick Installation Guide included with the router.

Helpful Hints...

First time users are recommended to run the **Setup Wizard**. Click the [Setup Wizard](#) button and you will be guided step by step through the process of setting up your ADSL connection.

If you consider yourself an advanced user or have configured a router before, click **Setup->Internet Setup** to input all the settings manually.

[More...](#)

**WELCOME TO D-LINK SETUP WIZARD**

This wizard will guide you through a step-by-step process to configure your new D-Link router and connect to the Internet.

- **Step 1 :** Change Device Login Password
- **Step 2 :** Set Time and Date
- **Step 3 :** Setup Internet Connection
- **Step 4 :** Configure Wireless Network
- **Step 5 :** Completed and Apply

3

**STEP 1: CHANGE DEVICE LOGIN PASSWORD → 2 → 3 → 4 → 5**

To help secure your network, D-Link recommends that you should choose a new password. If you do not wish to choose a new password now, just click "Skip" to continue. Click "Next" to proceed to next step.

Current Password :

New Password :

Confirm Password :

4

**1 → STEP 2: SET TIME AND DATE → 3 → 4 → 5**

The Time Configuration option allows you to configure, update, and maintain the correct time on the internal system clock. From this section you can set the time zone that you are in and set the NTP (Network Time Protocol) Server. Daylight Saving can also be configured to automatically adjust the time when needed.

SYSTEM TIME

System time: Sun Jan 1 0:34:7 2012

Time Zone: (GMT-12:00) International Date Line West ▾

DayLight: LocalTIME ▾

Mode: Copy Computer time ▾

5

Back

Next

Cancel

1 → 2 → **STEP 3: SETUP INTERNET CONNECTION** → 4 → 5

Please select your WAN Physical Type.

WAN Physical Type :

ISP

Please select your Country and ISP (Internet Service Provider) from the list below. If your Country or ISP is not in the list, please select "Others".

6

Country :

Internet Service Provider :

Protocol :

Connection Type :

VPI : (0-255)

VCI : (32-65535)

PPPoE

Please enter your Username and Password as provided by your ISP (Internet Service Provider). Please enter the information exactly as shown taking note of upper and lower cases. Click "Next" to continue.

7

Username :

Password :

8

Confirm Password :

9

10

1 → 2 → 3 → **STEP 4: CONFIGURE WIRELESS NETWORK** → 5

Your wireless network is enabled by default. You can simply uncheck it to disable it and click "Next" to skip configuration of wireless network.

Enable Your Wireless Network

Your wireless network needs a name so it can be easily recognized by wireless clients. For security purposes, it is highly recommended to change the pre-configured network name.

Wireless Network Name (SSID):

(1~32 characters)

username

Select "Visible" to publish your wireless network and SSID can be found by wireless clients, or select "Invisible" to hide your wireless network so that users need to manually enter SSID in order to connect to your wireless network.

Visibility Status :

Visible Invisible

In order to protect your network from hackers and unauthorized users, it is highly recommended you choose one of the following wireless network security settings.

Security Level :

None

WEP

WPA-PSK

WPA2-PSK

Security Mode: WPA-PSK

Select this option if your wireless adapters support WPA-PSK.

Now, please enter your wireless security key.

password

WPA2 Pre-Shared Key :

(8-63 characters, such as a~z, A~Z, or 0~9, i.e. '%Fortress123&')

Note: You will need to enter the same key here into your wireless clients in order to enable proper wireless connection.

11

Back

Next

Cancel

1 -> 2 -> 3 -> 4 -> STEP 3: COMPLETED AND APPLY

Setup complete. Click "Back" to review or modify settings. Click "Apply" to apply current settings.

If your Internet connection does not work after apply, you can try the Setup Wizard again with alternative settings or use Manual Setup instead if you have your Internet connection details as provided by your ISP.

SETUP SUMMARY

Below is a detailed summary of your settings. Please print this page out, or write the information on a piece of paper, so you can configure the correct settings on your wireless client adapters.

Time Settings :	Copy from Computer
WAN Physical Type :	DSL/VDSL
VPI / VCI :	8/35
Protocol :	PPPoE
Connection Type :	L2L
Username :	
Password :	
Wireless Network :	Enabled
Wireless Network Name (SSID) :	
Visibility Status :	Visible
Encryption :	WPA2-PSK/AES (also known as WPA2 Personal)
Pre-Shared Key :	

12